

Chella

Stylish and versatile recessed polycarbonate luminaire or exit sign with LED option.

Chella is an affordable recessed polycarbonate luminaire available in long life LED or 8W Fluorescent versions.

Supplied in White as standard, the Chella range of luminaires are available in chrome or brass to order.

Chella luminaires all utilise a hinged gear tray for ease of installation and the range of products includes mains, 3 hour maintained and non-maintained emergency versions with slave, addressable and self-test emergency options available.

Chella's design allows all versions to be utilised as a stylish edge-lit exit sign by specifying the optional legend. The attention-to-detail is illustrated with the effective light-pipe design, which enables the charge LED indicator to be clearly visible.

Other options available for Chella include slave versions for central battery or static inverter systems, self test and intelligent addressable gear.




Chella with white trim

Mains Luminaires

Cat No.	Lamp	Lumens	Kg
CHE1X8	1X8W 300mm	-	1.00Kg
CHE2X8	2X8W 300mm	-	1.00Kg
CHE11	11W TC-S	-	1.00kg

Emergency Luminaires

Cat No.	Mode/Lamp	Lumens*	Kg
CHE8/NM3	 NM3 8W 300mm	80E 120S 180H	1.50Kg
CHE8/M3	M3 8W 300mm	80E 120S 180H	1.80Kg
CHE2X8/NM3	NM3 2x8W 300mm	240E 360S	1.55Kg
CHE/LED/M3 NEW	LED M3	-	1.80Kg

Slave Luminaires

Cat No.	Mode/Lamp	Lumens*	Kg
CHE8/#/D	Slave 8W AC/DC Slave	275	1.00Kg
CHE/LED/#/D NEW	Slave LED	-	1.30kg

* Emergency Lumens

Specify 24, 50, 110 or 230 Volts AC/DC System Voltage. LED Slaves are suitable for 110V and 220V AC/DC systems

* For other durations, specify the required time period e.g. /NM3 becomes /NM1 for 1 hour duration

Dimensions: Length 380mm x Width 150mm

Edge-Lit Versions: Length 380mm x Width 150mm

Cut-Out: Length: Length 360mm x Width 130mm (70mm Min Ceiling Void)

Viewing Distances: 27 metres

Legend: Length 300mm x Width 173mm

Chella with chrome trim



Chella with brass trim and recessed legend (IP20)

Viewing distance 32 metres



Options Suffix:

- /H High Output
- /E Economy Output
- /S Standard Output
- /BR Brass Finish
- /CH Chrome Finish
- /HPF Power Factor Corrected
- /HF High Frequency Ballast
- /ES Electronic Start
- /AD Intelligent Addressable Luminaire
- /ST Self Testing Luminaire
- /EX Exit Version (IP20)