



# Savona

Savona with

chrome finish

# Edge-lit exit signs in single and double-sided versions

Savona is an edge-lit exit sign available in a range of high quality finishes. The smooth lines of the new Savona create a product of contemporary design which lends itself for use in many prestigious installations.

Models featuring both fluorescent and high output white light emitting diodes (LED) are available. LED's have the advantage of a long life combined with a very low maintenance requirement. Which ever light source you choose, Savona offers an elegant exit sign with superb performance.

The flame retardant Plasi-Glas legend panel suspends below the lamp and its light conducting properties ensure even and clear illumination of the panel.

The Savona body is supplied separately from the legend which is assembled with just two screws. This makes ordering single or double-sided signs very simple. If you require a single sided sign simply add the relevant legend number to the product code e.g. SAV8/NM3/L19. If you require a double-sided sign the product code would be SAV8/NM3/L19/D.

There are two Legend depths available - 270mm as standard or 135mm for areas where height is restricted.



Viewing distances 27 metres (135mm legend)

Viewing distances 40 metres (270mm legend)

# Mains Luminaires

Cat No.	Lamp	Lumens	Kg
SAV8	8W 300mm	-	2.90

#### **Emergency Luminaires**

Cat No.	Mode/Lamp	Lumens*	Kg
SAV8/NM3	NM3 8W 300mm	120	3.00
SAV8/M3	M3 8W 300mm	120	3.20

## **Emergency LED Luminaires**

Cat No.	Mode/Lamp	Lumens*	Kg
SAV/LED/M3	M3 LED	-	3.20

## Slave Luminaires

Cat No.	Mode/Lamp	Lumens*	Kg
SAV8/#/D	Slave 8W 300mm Sign	275	2.90

<sup>\*</sup> Emergency Lumens

**Dimensions:** Length 445mm x Width 90mm x Depth 340mm **Recess Version Dimensions:** Length 502mm x Width 152mm

Recess Version Dimensions Cut Out: Length 428mm x Width 135mm x Depth 85mm

# Options Suffix:

/R Recessed Trim
/CH Chrome Finish
/WH White Finish
/BR Bross Finish

/AD Intelligent Addressable Luminaire

**/ST** Self Testing Luminaire

/RAB Right angled mounting bracket





<sup>#</sup> Specify 24, 50, 110 or 230 Volts AC/DC System Voltage

<sup>\*</sup> For other durations, specify the required time period e.g. /NM3 becomes /NM1 for 1 hour duration